


TDA7227

SINGLE-CHIP AM/FM RADIO WITH FRONT-END

ADVANCE DATA


- BUILT-IN FM F/E AND AM/FM IF
- AM DETECTOR COIL AND IF COUPLING CAPACITOR ARE NOT NECESSARY
- WIDE OPERATING VOLTAGE RANGE (1.8 - 7V)
- LED DRIVE CIRCUIT FOR TUNING INDICA-TOR



DESCRIPTION


TDA7227 is a mono AM/FM one chip tuner ICs which is designed for portable radios, clock radios and radio cassette recorders.

PIN CONNECTIONS



December 1992 1/5

BLOCK DIAGRAM



ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	Value	Unit	
Vs	Supply Voltage	9	V	
I _{LED}	LED Current	10	mA	
VLED	Led Voltage	10	V] [
T _{oper}	Operating Temperature	- 25 to 75	°C	- 10-
T _{stg}	Storage Temperature	-55 to 150	°C	7227

RECOMMENDED OPERATING CONDITION AT T_A = 25°C

Symbol	Parameter	Value	Unit
Vs	Supply Voltage	1.8 to 7	V
T _{oper}	Operating Temperature	- 20 to 60	°C

ELECTRICAL CHARACTERISTICS

FM IF : f = 10.7MHz, f = + 22.5kHz, $f_m = 1kHz$

 $AM \hspace{0.5cm} : f=1MHz, \, m=30\%, \, f_m=1kHz$

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
Vs	Supply Voltage		1.8	3	7	٧
Icc	Supply Current	V _{IN} = 0, FM mode V _{IN} = 0, AM mode		9 7		mA mA
V _{IN} (lim)	FM F/E Input Limiting Voltage	- 3dB limiting		10		dBμ

FM SECTION


V _{IN} (lim)	Input Limiting Voltage	- 3dB limiting	44	dBμ
Vo	Recovered Output Voltage	$V_{IN} = 80 dB\mu$	80	mV
S/N	Signal to Noise Ratio	$V_{IN} = 80 dB\mu$	70	dB
THD	Total Harmonic Distorsion	$V_{IN} = 80 dB\mu$	0.4	%
AMR	AM Rejection Ratio	V _{IN} = 80dBμ	50	dB

AM SECTION

G _V	Gain	$V_{IN} = 26dB\mu$	40	mV
Vo	Recovered Output Voltage	V _{IN} = 60dBμ	60	mV
S/N	Signal to Noise Ratio	$V_{IN} = 60 dB\mu$	44	dB
THD	Total Harmonic Distorsion	V _{IN} = 60dBμ	1.0	%
Ro	Pin 12 Output Resistance	FM mode AM mode	5 5	kΩ kΩ

7227-03.TBL


TEST CIRCUIT



COIL DATA


Coil N°	f	L	Со	Qo		Turns				Wire	Ref. *	
Con N	(Hz)	(μH)	(pF)	Q()	1 - 2	2 - 3	1 - 3	1 - 4	1 - 6	(mm∅)	Nei.	
L1 FM RF	100M			100				$2\frac{1}{2}$		0.5 UEW		
L2 FM OSC	100M			100			2 3/4			0.5 UEW		
L3 AM OSC	796k	288		115	13	73				0.08 UEW	S - 4147 - 1356 - 045]
T1 FM MIX	10.7M		75	115			12		1	0.12 UEW	S - 0133 - 309 - 045] <u>r</u>
T2 AM MIX	455k		180	120			180		15	0.08 UEW	S - 2150 - 2162 - 165	7-04
T3 FM DET	10.7M	·	47	165			16			0.09 UEW	S - 2153 - 4095 - 132	7227

* S : Sumida Electronic CO, Ltd.



PACKAGE MECHANICAL DATA

18 PINS - PLASTIC DIP



Dimensions		Millimeters			Inches	
Dimensions	Min.	Тур.	Max.	Min.	Тур.	Max.
a1	0.254			0.010		
В	1.39		1.65	0.055		0.064
b		0.46			0.018	
b1		0.25			0.010	
D			23.24			0.914
Е		8.5			0.335	
е		2.54			0.100	
e3		20.32			0.800	
F			7.1			0.280
i			3.93			0.155
L		3.3			0.130	
Z		1.27	1.59		0.050	0.062

DIP18.TBL

Information furnished is believed to be accurate and reliable. However, SGS-THOMSON Microelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No licence is granted by implication or otherwise under any patent or patent rights of SGS-THOMSON Microelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. SGS-THOMSON Microelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of SGS-THOMSON Microelectronics.

© 1992 SGS-THOMSON Microelectronics - All Rights Reserved

SGS-THOMSON Microelectronics GROUP OF COMPANIES

Australia - Brazil - China - France - Germany - Hong Kong - Italy - Japan - Korea - Malaysia - Malta - Morocco The Netherlands - Singapore - Spain - Sweden - Switzerland - Taiwan - United Kingdom - U.S.A. ORDER CODE